# MT 645 VP



# & Cobra®

# LICENSE-FREE WALKIE-TALKIE Handfunkgerat Transceptor Talkie Walkie



## Up to 8 km range

Compact design with extended range.

### VOX

For hands-free operation.

#### Call Alert

Provides a recognizable alert for incoming calls.

# Roger Beep

Confirmation tone indicates to others it's clear to talk.





# MT 645 VP

#### Features Benefits

UHF/FM	Ultra-clear long distance reception.				
8 KM Range	Up to 8 KM range. (Range will vary depending on terrain and conditions).				
8 Channels	Front panel push buttons provide easy access to all 8 channels.				
121 Privacy Codes	38 CTCSS (Continuous Tone Coded Squelch System) codes and 83 DCS (Digitally Coded Squelch) codes provide a total of 121 privacy codes. 968 privacy combinations are possible when the 8 channels are combined with the 121 privacy codes.				
VOX (Voice Activated Transmission)	User's voice is detected and the radio transmits without the need to press any buttons, freeing the user's hands for other tasks. 5 VOX sensitivity levels allow user to select at which point the radio will detect their voice.				
Scan	Allows user to scan either channels, CTCSS privacy codes within a channel, or DCS codes within a channel to locate conversations in progress.				
Call Alert (5 selectable tones)	Provides up to 5 easily recognizable call alert tones for incoming calls.				
Roger Beep Tone (selectable on/off)	Confirmation tone indicates the completion of the user's transmission, and signals to others it is clear to talk. This feature is selectable and can be turned on or off.				
Key Lock	When activated, provides key pad security eliminating accidental channel changes.				
Power Saver	A unique circuit extends the life of your batteries. If there are no transmissions within 10 seconds, the unit will automatically switch to battery saver mode.				
Auto Squelch	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.				
LCD Display	Easy to view display provides the radio's status at a glance.				
6 AA NiMH Rechargeable Batteries	Radios can also be used with 3 AA alkaline batteries per radio (not included).				
Micro-USB Charging Cable Charge Jack	Charges supplied rechargeable batteries inside radios. Charger accommodates 1 or 2 radios. Speaker/Microphone/Allows use of "Y' wall mount charger or earphone speaker/microphones (not included) for "hands-free" operation.				
Multilingual Manual	Includes a 17 language instruction manual.				
Belt Clip	Secures your microTALK radio while on the go.				
No Licence or Service Fees	Licence or Service Fees High quality band frequencies with no fees.				

#### **Unit Specifications - General**

Unit Dimensions:	6.05" H x 2.41"W x 1.55" H 153.62mm x 61.3mm x 39.46mm	SKU#: UPC#:	MT 645 VP 0 28377 91001 2	Dimension:	11.95" H x 8.32"W x 13.09" H 303.56mm x 211.41mm x 332.38mm
Unit Weight:	3.44 oz. (97.5 g.)	Batteries:	3 AA per radio (not included)	Master Pack	6.21 lbs. (2818 g.)
RF Output:	500 mW	Masterpack Barcode:	1 0028377 91001 9	Weight:	
Channels:	8	Master Pack Qty:	4	*Specifications subject to change without notice*  *All dimensions (H x W x D) except where noted*	
	CH1 = 446.00625 MHz 2 = 446.01875 3 = 446.03125 4 = 446.04375	Package Dimension:	11.10" H x 7.60"W x 3.61" H 282mm x 193mm x 91.67mm		
	4 = 446.04373 5 = 446.05625 6 = 446.06875 7 = 446.08125 8 = 446.09375	Package Weight:	21.80 oz. (618 g.)		

## 17 Language Manual Includes:





Swedish

©2013 Cobra Electronics Europe Limited, Dungar House,
Northumberland Avenue, Dun Laoghaire, County Dublin, Ireland
Cobra® microTALK® Northing Compact Close to a Cobra® and the spake does

 ${\sf Cobra}^{\$}, {\sf microTALK}^{\$}, {\sf Nothing\ Comes\ Close\ to\ a\ Cobra}^{\$} \ and\ the\ snake\ design\ are\ registered\ trademarks\ of\ Cobra\ Electronics\ Corporation,\ USA.$ 

Cobra Electronics Corporation™ is a trademark of Cobra Electronics Corporation, USA.

 $\mathsf{CEEL^{TM}}$  is a trademark of Cobra Electronics Europe LTD.



